

Totally Focused. Totally Independent.

Technical Guide

ECO40 4 B



The world's largest independent producer of alternators 1 – 5,000kVA



Standards

Alternators are designed and produced within an ISO 9001 environment. The entire series is manufactured according to, and complies with, the most common specifications such as CEI 2-3, IEC 34-1, EN 60034-1, VDE 0530, BS 4999-5000, NF 51.111, CAN/CSA-C22.2 No14-95-No100-95, NEMA MG 1-2011, ISO 8528-3. Other standards such as UL1446, UL 1004/4 and /B are available on request.

Windings and Performances

All windings are 2/3rds pitch to eliminate triplen harmonics within the voltage waveform and to avoid excessive neutral currents in certain parallel operating conditions. A fully interconnected aluminium or copper damper cage is supplied on the rotor of all models (excluding the ECP3 series).

12 wire reconnectable:

50Hz - 380V to 440V and 220/110V to 240/120V (de-rates may apply at certain voltages) 60Hz - 380V to 480V and 220/110V to 240/120V (de-rates may apply at certain voltages)

6 wire reconnectable:

50Hz - 380V to 440V and 220V to 240V (de-rates may apply at certain voltages) 60Hz - 380V to 480V and 220V to 240V (de-rates may apply at certain voltages)

	Stan	dard	Special (dedicated)				
Configurations	12 wire Reconnectable	6 wire Reconnectable	380V and 600V 60Hz	690V 50/60Hz	220-240V 1ph 50Hz	220-240V 1ph 60Hz	
ECP3 to ECO38	Std	Option	Option	Option	Option	Option	
ECO40 to ECO46	Std	Option	Option	Option	Option (to ECO40)	Option (to ECO40)	
Insulation materials	Class H	Class H	Class H	Class H	Class H	Class H	
High efficiency	Std	Std	Std	Std	Std	Std	
High motor starting	>300%	>300%	>300%	>300%	>300%	>300%	
THD (Total Harmonic Distortion)	Typically <3.5% full load L-L	Typically <3.0% full load L-L	Typically <3.5% full load L-L	Typically <3.5% full load L-L	Typically <4.5% full load L-N	Typically <4.5% full load L-N	
Interference suppression	VDE 0875 G/N/K, EN61000-6-3, EN61000-6-2, others available on request						

Winding Protection

There are various degrees of protection for the windings following the standard impregnation process, as can be seen here. The TOTAL+ butadienic black flexible coating is recommended for arduous applications.

Winding Protection:	STANDARD	STANDARD+	GREY	GREY+	TOTAL+
ECP3	Std	Option	Option	Option	Option
ECP28 and ECP32	-	Std	Option	Option	Option
NPE32, ECP34 to ECO46	-	-	Std	Option	Option



Grey treatment (marinization) on the left, TOTAL+ treatment shown on the right. The EG43 grey varnish, is an high temperature insulating enamel that forms a tough and flexible film, with excellent moisture and chemical protection. It is water and oil proof, and also protects windings from abrasion. It is applied spraying an over coating layer over the impregnated winding, or dipping the stator in a varnish barrel for superior treatments

The TOTAL+ is a protection system that makes Mecc Alte special. It is the ultimate winding treatment that offers truly superior performances when the environment is really harsh, or the application very demanding. The TOTAL+ is also extremely resistant to the particle abrasion as it adsorbs the impacts.

Protection for Environment

In addition to protection on the windings themselves, the alternators can have increased ingress protection. Standard levels are IP23 with further upgrades available to include inlet filters, IP43 and IP45: 7% de-rates apply on inlet filters and IP43 protection. 20-30% de-rates apply for IP45 depending on alternator model.

Additional air exit louvres (called IP23+) are optionably retrofittable in the overall ECP32 to ECO 46 range, in order to comply to the most strict marine regulations.



Construction

The robust mechanical structure withstands up to 5G in any direction and 9G vertically and its design permits easy access to the connections and components during routine maintenance check-ups. The mechanical design has used the most advanced FEM techniques. The materials used are: FEP12 steel for the frame, C45 steel for the shaft and cast iron or aluminum pressure die cast for the end-brackets: fans are aluminum die casted either nylon fiber glass loaded, UL compliant materials. Rotors are dynamically balanced according grade 2.5 of ISO 1940-1.

Terminals and Terminal Box

Easy access to regulators is assured through a pull out drawer or a drop down panel to allow safer adjustment. Large terminal boxes allow easy access of power cables, in the ECO43 and ECO46 higher power ranges the terminal allow the convenient choice of power cable or busbar connection with versatility of entry and connection. Current transformers are available as an option on series ECO 40, 43 and 46 with single or dual output.



Excitation and Regulation Systems

All ECP/ECO series have MAUX auxiliary winding to power the digital regulator. Both DSR and the DER1 are available to connect to PC through the DxR2 USB interface and DxR TERMINAL software to interrogate/download alarms & settings for analysis or for cloning other regulators. DER2 has got an integrated USB connection and can be connected to the PC without any optional connection boards. More settings such as LAMS, digital RAM based synchronous external control and soft start are obtainable through the DxR connection. Simple analogue potentiometers are available for the more usual adjustments.

Excitation Systems	DSR	DER1	DER2
ECP3 to ECO38	Std	Option	Option
ECO40 to ECO46	-	Std	Option
Parallel Operation	V	V	V
Mains Parallel	v	√.	V
3 Phase Sensing (rms)	-	V	V
Accuracy	+/-1%	+/-0.5%	+/-0.5%
Remote Voltage Control	v	V	v
Alarm Log	v		V
Analogue and Digital Configurable	V	V	V
LAMS (Load Acceptance V/f)	v		V
APO (Active Protection Output)	v	V	v
Soft Start	v		
High dynamic response	-	-	v
USB connection without external boards	-	-	

For a given motor start duty a smaller machine may be selected – also enhanced by low sub-transient reactance values for non-linear loads. The whole range from 6.5 to 3400kVA is capable of >300% sustained short circuit current for up to 20 seconds.

General Data

Optional PMG3

PMG3 can be retro fit or factory fit on ECO 40, 43 and 46 series. This smart MeccAlte design allows an easy fix kit, through a tapered cone coupling and a simple replacement of the rear air louvre. PMG3 is also available on ECO 38, when ordered from the factory.

The complete AVR range is fully compatible with both MAUX and PMG3 systems, this minimises spare part management and flexibility of stock as one AVR suits all applications. The PMG3 is delivering the same amount of kVA available with the MAUX.



Accessories

Additional optionals can be fit on our alternator series, such as PTC thermistors or PT100 both on windings and bearings, space heaters, high and low profile of terminal boxes (on most series), air filter clogging sensors, rotating diode bridge failure sensor (RBD), power factor controller for parallel operation (PFR/2), parallel devices (standard from ECO 40), air filters, IP43 and IP45 protections, marine IP23 + protection for SOLAS requirements and many others.

Deration coefficients

			Ambient tempe	erature (Celsius)		
Altitude (meters)	25	40	45	50	55	60
<i>≤ 1000</i>	1.07	1	0.96	0.93	0.91	0.89
> 1000 ≤ 1500	1.01	0.96	0.92	0.89	0.87	0.84
> 1500 ≤ 2000	0.96	0.91	0.87	0.84	0.83	0.79
> 2000 ≤ 3000	0.9	0.85	0.81	0.78	0.76	0.73

Notes on short circuit curves

The indicated coefficients have to be used to correct the three phase short circuit curves values as a function of the rated voltage.

The indicated coefficient have to be used to correct the three phase short circuit curves values as a function of the type of short circuit voltage.

50	Hz	60	Hz
Voltage	Factor	Voltage	Factor
380	0.93X	415	0.85X
400	1X	440	0.90X
415	1.04X	460	0.95X
440	1.10X	480	1X

3 phase 2 phase L-L 1 phase L-N Istantaneous 1X 0.87X 1.30X Minimum 1X 1.80X 3.20X Sustained 1X 1.50X 2.50X Max Duration 20 sec. 10 sec. 4 sec

All the curves are shown for series or parallel star connection at 400V 50 Hz or 480V 60 Hz. If the unit is reconnected from series to parallel star, the additional coefficient is 2X. From series star to series delta, it is 1.72X. From series star to parallel delta, it is 3.44X.



General characteristics

Pole number	4	Insulation class	Н
Phase number	З	Protection class	IP23
Number of wires	12	NDE Bearing type	6318.2RS
Execution	Brushless	DE Bearing type	6322
Regulator type	DER-1/A	Maximum Overspeed	2250
Winding pitch	2/3	Altitude	≤ 1000
Code voltage reference	T0405P3	Balancing	IS01940-1

Ratings

400V - 50Hz @ 125/40°C - 0.8 PF - Standard				
		ECO40 354 B		
Rated power	kVA	500		
	kW	400		

Reactance & Time constants

Unsat	curated (ref. EN60034-4)		ECO40 3S4 B
Xd	Direct-axis synchronous reactance	%	258,7
X'd	Direct-axis transient reactance	%	21,7
X''d	Direct-axis subtransient reactance	%	11,8
Xq	Quadrature-axis synchronous reactance	%	111,8
X'q	Quadrature-axis transient reactance	%	111,8
X"q	Quadrature-axis subtransient reactance	%	27,3
X 2	Negative-sequence reactance	%	17,3
X0	Zero sequence reactance	%	3,1
Satur	ated		
Xd	Direct-axis synchronous reactance	%	214,7
X'd	Direct-axis transient reactance	%	18
X''d	Direct-axis subtransient reactance	%	9,79
Xq	Quadrature-axis synchronous reactance	%	92,8
X'q	Quadrature-axis transient reactance	%	92,8
X"q	Quadrature-axis subtransient reactance	%	22,7
X 2	Negative-sequence reactance	%	14,4
X0	Zero sequence reactance	%	3,1
Kcc	Short circuit ratio		0,4
T'd	Transient time constant	sec	0,14
T''d	Subtransient time constant	sec	0,021
T'do	Open circuit time constant	sec	2,8
Τα	Armature time constant	sec	0.031

Additional information

lo	Excitation current at no load	А	0,5
Ic	Excitation current at full load	А	3,4
Overlo	ad		1 hour in a 6 hours period 110% rated load
Overlo	ad per 20 sec.	%	300
Heat	lissipation	W	22833
Telepl	none Harmonic Factor - THF	%	<2
Wave	form Distors.(THD) full load LL/LN	%	2,4 / 2,5
Wave	form Distors.(THD) no load LL/LN	%	2,6 / 2,5

meccalte

Efficiencies @ 50 Hz

Models		400/230V 50Hz					
		0.25	0.5	0.75	1	1.1	
ECO40 3S4 B	%	90,3	93,9	94,8	94,6	94,4	







Transients voltage



In order to scale transient curves as a function of a power factor or voltage if not indicated, please proceed as follows:

Power Factor coefficient corrector (PFCC), to be used on power factor 0.6 curves:

PFCC=sin(ARCcos (PFnew))/0.8

Example. The PFCC at power factor 0.3 is 1.192 [PFCC= sin(ARCcos (0.3))/0.8]. This means that the voltage fall at a given power at pf 0.3 is equivalent to the one that can be read on the pf 0.6 curve if the load is considered 1.192 times bigger (19% higher value.).

In this example, a 100 kVA load insertion at pf 0.3 is equivalent in voltage fall to a 119kVA load insertion at pf 0.6.

Voltage coefficient corrector (VCC):

VCC=(400/Vnew)2 if 50 Hz; VCC=(480/Vnew)2 if 60 Hz

Example. VCC at 415V 60 Hz is 1.338 [VCC=(480/415)^2]. This means that the voltage fall at a given power at 415V is equivalent to the one that can be read on the power factor 0.6 curve if the load is considered 1.338 times bigger (33% higher value.).

In this example, a 100 kVA load insertion at 415V is equivalent in voltage fall to a 133kVA load insertion at 480V.

..............

50Hz Short circuit decrement curves - No load excitation at rated speed



ECO40 3S4 B

*Please refer to tables at page 6



Additional Characteristics

Data		EC040 3S4 B		
		50 Hz		
Damper cage		Copper		
Stator Winding Resistance (20°C)	Ω	0,014		
Rotor Winding Resistance (20°C)	Ω	5,176		
Stator Exciter Resistance (20°C)	Ω	8,85		
Rotor Exciter Resistance (20°C)	Ω	0,317		
Weight of complete generator	kg	1208,0		
Unbalanced magnetic pull	kN/mm	6,5		
Air flow	m ³ /min	54,0		
Noise level at 1m/7m	dB(A)	94/82		

PQ Diagram



ECO40 4 B



ECO40 3S4 B





ECO40 4 B



ECO40 3S4 B





ECO40 4 B



Notes

Mecc Alte SpA (HQ)

Via Roma 20 - 36051 Creazzo Vicenza - ITALY T: +39 0444 396111 F: +39 0444 396166 E: info@meccalte.it aftersales@meccalte.it

United Kingdom

Mecc Alte U.K. LTD 6 Lands' End Way Oakham Rutland LE15 6RF T: +44 (0) 1572 771160 F: +44 (0) 1572 771161 E: info@meccalte.co.uk aftersales@meccalte.co.uk

U.S.A. and Canada

Mecc Alte Inc. 1229 Adams Drive McHenry, IL, 60051 T: +1 815 344 0530 F: +1 815 344 0535 E: info@meccalte.us aftersales@meccalte.us

France

Mecc Alte International S.A. Z.E.La Gagnerie 16330 ST.Amant de Boixe T: +33 (0) 545 397562 F: +33 (0) 545 398820 E: info@meccalte.fr aftersales@meccalte.fr

Mecc Alte Portable Via Roma

20 - 36051 Creazzo Vicenza - ITALY T: +39 0444 396111 F: +39 0444 396166 E: info@meccalte.it aftersales@meccalte.it

T: +39 0444 1831295 F: +39 0444 1831306 E: info@meccalte.it aftersales@meccalte.it

Via Melaro

Spain

Mecc Alte España S.A. C/ Rio Taibilla, 2 Polig. Ind. Los Valeros 03178 Benijofar (Alicante) T: +34 (0) 96 6702152 F: +34 (0) 96 6700103 E: info@meccalte.es aftersales@meccalte.es

Germany

Mecc Alte Generatoren GmbH Ensener Weg 21 D-51149 Köln T: +49 (0) 2203 503810 F: +49 (0) 2203 503796 E: info@meccalte.de aftersales@meccalte.de

Far East

Mecc Alte (F.E.) PTE LTD 19 Kian Teck Drive Singapore 628836 T: +65 62 657122 F: +65 62 653991 E: info@meccalte.com.sg aftersales@meccalte.com.sg

China Mecc Alte Alternator Haimen LTD 755 Nanhai East Rd Jiangsu HEDZ 226100 PRC

Jiangsu HEDZ 226100 PRC T: +86 (0) 513 82325758 F: +86 (0) 513 82325768 E: info@meccalte.cn aftersales@meccalte.cn

Mecc Alte Power Products srl

2 - 36075 Montecchio

Maggiore (VI) - ITALY

Australia

Mecc Alte Alternators PTY LTD 10 Duncan Road, PO Box 1046 Dry Creek, 5094, South Australia T: +61 (0) 8 8349 8422 F: +61 (0) 8 8349 8455 E: info@meccalte.com.au aftersales@meccalte.com.au

meccalte

Zanardi Alternatori srl Via Dei Laghi

48/B – 36077 Altavilla

T: +39 0444 370799

F: +39 0444 370330

E: info@zanardialternatori.it

Mecc Alte India PVT LTD

Plot NO: 1, Sanaswadi

Dhamdhere Road Taluka

Vicenza – ITALY

India

Talegaon

Shirur, District

Pune - 412208

Maharashtra, India

T: +912137619600

F: +91 2137 619699 E: info@meccalte.in

aftersales@meccalte.in

www.meccalte.com